


Short user guide innovaphone IP230



Display

Symbol	Description
	Loudspeaker
	Microphone
	Call diversion
	Telephone locked
	Handset
	Headset
	Connection down
	Connection up



Keys

Key	...in idle state	...during connection
	Enter main menu, leave menu and save changes	Setup a conference
		Adjust volume of speaker
	Enter menu, confirm selection, enter	
	Arrow keys for orientation in menu	Left and right arrow to adjust volume
	Delete left character	
	Leave menu without saving changes	Terminate active call
	Enter to complete entries or confirm selection	
	Exit menu	Terminate active call
	Do not disturb, ring tone off	Mute, microphone off
	Displays in-bound call list	Consultation call
	Displays out-bound call list	Forward active call
	Starts hands-free calling	Speaker on, change to hands-free mode

















Actions

Action	Status	Keys	Description
Accept call		 pick up	The display shows caller and called party
Reject call			Caller gets a busy tone
Terminate call		 hang up, 	The active call is terminated
Make call		0...9, then 	All numbers can be entered after picking up the handset
Redial		 ,  then 	Displays the last in-bound calls, use  to select the final entry
Callback		 ,  then 	Provides the last incoming calls for callback, use  to select the final entry
Speaker on			Toggles speaker on and off
Switch to hands-free mode		 hold and hang up 	From handset mode; symbol  appears in display
Switch to handset mode		 pick up	From hands-free mode; symbol  appears in display
Mute			Symbol  appears blinking in display
Consultation call		 , 1...9 dial	Use  to terminate consultation call and return to first connection
Switch between calls		 , 1...9 dial	Use   to switch between two calls
Conference		 , 1...9 dial, 	To cancel the conference, press  again
Transfer call		 , 1...9 dial and hang up 	For transfer before the consultation call is connected, hang up
Call completion on busy subscriber		 , 	The phone rings as soon as the callback is possible
Call completion on no answer		 , 	The phone rings as soon as the remote phone is active again
Automatic redial		 ,  , 	Redials the last call every 30 seconds for 20 minutes
Pick-Up		 , 1...9, 	Picks up the call to the phone number you have entered





Function key configuration

Function		Display	Description
Dial			Dials the configured number
Call Forwarding		0: 1: 2: 3: Off	Configuration of automatic call forwarding Up to 4 different destinations can be configured Call forwarding unconditional on busy or on no reply  shows call forwarding on busy or no reply. Call forwarding unconditional shows the complete number in display
Lock		0: 1:	Locks the phone, only out-bound calls using dial pad are possible  shows the phone lock
Ringer off		0: 1:	Ring tone off, status will be shown in telephone display 
Call waiting		0: 1:	Off: if phone is active, in-bound call get busy signal On: if phone is active, in-bound call will be announced
Hide own number		0: 1:	Off: provide own number in out-bound calls On: hide own number in out-bound calls
Headset		0: 1:	Enables and disables the use of headset  shows that the headset is active
Partner			 direct call   Pickup: Shows the call information of your partner   Busy status on partner side
Pickup			Shows in-bound call to group members  pick up a single call In case of multiple calls, the list of pending call is displayed and permit the selection of calls; use  to select the call you will take
Registration			Registration of additional user for the phone <input type="checkbox"/> new user becomes active user <input type="checkbox"/> main user still the active user
Unregistration			Unregistration of the co-user
Switch			Change active users, after which all settings for that user are active
Hot desking			Register co-user by entering name, number and password Press  again to unregister this user
Message waiting			There is a message for you  to enter the message system
Transfer			Connects the two calls that you are currently handling
Redirect			 Blind transfer to the defined number  Redirect to defined number




↑ ↑ Enter your own configuration in these fields






Partner keys

The partner keys can be found on the right hand side of the telephone IP230. There are 10 partner keys available on the device. Using appropriate additional modules the number of partner keys can be extended by a further 30 keys. Up to 3 additional modules can be connected to the telephone, so that up to 100 partner keys are available.

In principle the partner keys can be programmed with all functions, which are also available for the function keys next to the display. The current status is not indicated on the display instead an LED is integrated into the key. This means the key block is optimally appropriate for the function as partner key.

Status	Function	Description
 off	Dial	When this key is pressed, the configured partner calling number is dialled in hands free mode. Picking up the handset means the call is transferred to handset. The key can also be used to transfer calls.
 blinking	Pick-Up	The partner's telephone is ringing. The call can be transferred to own telephone by pressing the key and can be received as usual.
 on	User busy	The partner telephone is busy. This phone can only be reached or transferred to if the call-waiting function is activated.

All described functions are related to the IP200 phone connected to an innovaphone PBX.

The configuration of the phone has to be done over Web interface. Use this key  to enter the menu, select for  administration and confirm with , select information and confirm again. The first line shows the actual IP address of your phone device. Enter this IP address in the address field of your Web browser. Note that the configuration is password protected.



The advanced operating manual will be available for free as a PDF file in the download area of www.innovaphone.com.